

The coil chart shows applicable voltages for various frequencies. Specify voltages and frequencies as listed below when ordering. Consult factory for voltages and frequencies not listed.

SERIES 30 COIL CHART

A.C. VOLTAGES		D.C. VOLTAGES	NON-MOLDED COIL NO.	MOLDED COIL NO.
60 HZ.	50 HZ.			
6	5.2	2	3C-101-A24	3C-1-K24
7.8	6.7	2.5	3C-102-A24	3C-2-K24
9	7.7	3	3C-103-A24	3C-3-K24
			3C-104-A24	3C-4-K24
			3C-105-A24	3C-5-K24
12	10	4	3C-106-A24	3C-6-K24
16	14	5	3C-107-A24	3C-7-K24
18	15	6	3C-108-A24	3C-8-K24
24	20	7.8	3C-109-A24	3C-9-K24
27	23	9	3C-110-A24	3C-10-K24
37	32	12	3C-111-A24	3C-11-K24
48	40	15	3C-112-A24	3C-12-K24
100	85	33	3C-113-A24	3C-13-K24
73	60	24	3C-114-A24	3C-14-K24
82	70	28	3C-115-A24	3C-15-K24
120	100	40	3C-116-A24	3C-16-K24
145	127	48	3C-117-A24	3C-17-K24
140	120	47	3C-118-A24	3C-18-K24
240	204	80	3C-119-A24	3C-19-K24
325	280	115	3C-120-A24	3C-20-K24
345	295	120	3C-121-A24	3C-21-K24
480	410	160	3C-122-A24	3C-22-K24
575	500	200	3C-123-A24	3C-23-K24
630	540	230	3C-124-A24	3C-24-K24
360	310	125	3C-125-A24	3C-25-K24
204	175	65	3C-126-A24	3C-26-K24
110	95	38	3C-127-A24	3C-27-K24
650	560	240	3C-128-A24	3C-28-K24
185	157	60	3C-133-A24	3C-33-K24
63	54	20	3C-134-A24	3C-34-K24
79	68	26	3C-135-A24	3C-35-K24
76	65	25	3C-136-A24	3C-36-K24

EXPORT COILS

14	12	4.8	3CE-106-A24	3CE-6-K24
28	24	9.5	3CE-109-A24	3CE-9-K24
57	48	19	3CE-112-A24	3CE-12-K24
128	110	42	3CE-116-A24	3CE-16-K24
255	220	90	3CE-119-A24	3CE-19-K24
280	240	95	3CE-120-A24	3CE-20-K24
440	380	150	3CE-122-A24	3CE-22-K24
515	440	185	3CE-123-A24	3CE-23-K24

DIODE RECTIFIED COILS

120	110 & 120		3CD-116-A24	
240	220 & 240		3CD-130-A24	
24	24		3CD-131-A24	